



**CORDIAM srl**

Via Madonna, 19

22070 Guanzate (CO) - Italia-

Tel +39 031 97 72 74 - Fax +39 031 97 66 15

e-mail: info@cordiam.it - www.cordiam.it

## BT800



Tensione		
Voltage	V	380 - 400
Spannung		
Potenza		
Power	W	2X3420
Leistungsaufnahme		
Velocità a vuoto		
Idle speed	min <sup>-1</sup>	120 - 200 - 310 - 450
Leerlaufdrehzal		
Velocità a carico		
Speed (@ rated power)	min <sup>-1</sup>	80 - 130 - 200 - 300
Lastdrehzahl		
Coppia		
Torque (@ rated power)	Nm	530 - 330 - 207 - 144
Drehmoment		
Capacità		
Capacity	mm	100 - 800
Bohrkronen		
Frizione meccanica		dischi in bronzo
Mechanical clutch		brass rings
Sicherhetskupplung		mit bronzescheiben
Limitatore di spunto		2 stadi
Soft start		2 steps
Anlaufstrombegrenzer		2 stufen
Peso		
Weight	Kg	28
Gewicht		