



**CORDIAM srl**

Via Madonna, 19  
22070 Guanzate (CO) - Italia-  
Tel +39 031 97 72 74 - Fax +39 031 97 66 15  
e-mail: info@cordiam.it - www.cordiam.it

## BT 1000



Tensione		
Voltage	V	380 - 400
Spannung		
Potenza		
Power	W	2X3420
Leistungsaufnahme		
Velocità a vuoto		
Idle speed	min <sup>-1</sup>	100 - 150 - 250 - 350
Leerlaufdrehzal		
Velocità a carico		
Speed (@ rated power)	min <sup>-1</sup>	60 - 100 - 160 - 230
Lastdrehzahl		
Coppia		
Torque (@ rated power)	Nm	732 - 460 - 288 - 200
Drehmoment		
Capacità		
Capacity	mm	150 - 1000
Bohrkronen		
Frizione meccanica		dischi in bronzo
Mechanical clutch		brass rings
Sicherhetskupplung		mit bronzescheiben
Limitatore di spunto		2 stadi
Soft start		2 steps
Anlaufstrombegrenzer		2 stufen
Peso		
Weight	Kg	39
Gewicht		