



CORDIAM srl
 Via Madonna, 19
 22070 Guanzate (CO) - Italia-
 Tel +39 031 97 72 74 - Fax +39 031 97 66 15
 e-mail: info@cordiam.it - www.cordiam.it

TR 500



Tensione			
Voltage	V	380 - 400 50Hz	480 60Hz
Spannung			
Potenza			
Power	W	6000	6000
Leistungsaufnahme			
Velocità a carico			
Speed (@ rated power)	min ⁻¹	140 - 220 - 330 - 470	170 - 265 - 400 - 565
Lastdrehzahl			
Coppia			
Torque (@ rated power)	Nm	280 - 176 - 120 - 85	230 - 145 - 100 - 70
Drehmoment			
Capacità			
Capacity	mm	80 -500	80 - 500
Bohrkronen			
Frizione meccanica		dischi in bronzo	dischi in bronzo
Mechanical clutch		brass rings	brass rings
Sicherhetskupplung		mit bronzescheiben	mit bronzescheiben
Limitatore di sovraccarico		Nel motore	Nel motore
Overload limiter		Within the motor	Within the motor
Überlastungsbegrenzer		In der Motor	In der Motor
Peso			
Weight	Kg	25	25
Gewicht			